



**Note: This API call is for DOS and Win16 personality only. Use [Family API](#) for portability.**

2018/09/07 05:04 · prokushev · [0 Comments](#)

# Int 20H

## Version

1 and higher

## Brief

TERMINATE PROGRAM

## Family API

[DosExit](#)

## Input

```
CS = PSP segment
```

## Return

Never return

## Macro

```
INCLUDE DOS.INC  
  
TERMINATE
```

## Notes

Function is obsolete. Use [INT 21/AH=4Ch](#) instead

This function sets the program's return code (ERRORLEVEL) to 00h

## See Also

[INT 21/AH=00h](#) [INT 21/AH=4Ch](#)

## Note

Text based on [Ralf Brown Interrupt List Release 61](#)

<b>DOS API</b>	
Process manager	<a href="#">INT 20H</a> , <a href="#">INT 21H</a> : <a href="#">00H</a> , <a href="#">25H</a> , <a href="#">26H</a> , <a href="#">31H</a> , <a href="#">34H</a> , <a href="#">35H</a> , <a href="#">4BH</a> , <a href="#">4CH</a> , <a href="#">4DH</a> , <a href="#">50H</a> , <a href="#">51H</a> , <a href="#">52H</a> , <a href="#">55H</a> , <a href="#">62H</a> , <a href="#">INT 22H</a> , <a href="#">INT 27H</a> , <a href="#">INT 28H</a>
File manager	<a href="#">INT 25H</a> , <a href="#">INT 26H</a> , <a href="#">INT 21H</a> : <a href="#">0DH</a> , <a href="#">0EH</a> , <a href="#">0FH</a> , <a href="#">10H</a> , <a href="#">11H</a> , <a href="#">12H</a> , <a href="#">13H</a> , <a href="#">14H</a> , <a href="#">15H</a> , <a href="#">16H</a> , <a href="#">17H</a> , <a href="#">19H</a> , <a href="#">1AH</a> , <a href="#">1BH</a> , <a href="#">1CH</a> , <a href="#">21H</a> , <a href="#">22H</a> , <a href="#">23H</a> , <a href="#">24H</a> , <a href="#">27H</a> , <a href="#">28H</a> , <a href="#">29H</a> , <a href="#">2EH</a> , <a href="#">2FH</a> , <a href="#">32H</a> , <a href="#">3305H</a> , <a href="#">36H</a> , <a href="#">39H</a> , <a href="#">3AH</a> , <a href="#">3BH</a> , <a href="#">3CH</a> , <a href="#">3DH</a> , <a href="#">3EH</a> , <a href="#">3FH</a> , <a href="#">40H</a> , <a href="#">41H</a> , <a href="#">42H</a> , <a href="#">4300H</a> , <a href="#">4301H</a> , <a href="#">45H</a> , <a href="#">45H</a> , <a href="#">46H</a> , <a href="#">4EH</a> , <a href="#">4FH</a> , <a href="#">54H</a> , <a href="#">56H</a> , <a href="#">5700H</a> , <a href="#">5701H</a> , <a href="#">5AH</a> , <a href="#">5BH</a> , <a href="#">5c00H</a> , <a href="#">5c01H</a> , <a href="#">60H</a> , <a href="#">67H</a> , <a href="#">68H</a> , <a href="#">6900H</a> , <a href="#">6901H</a> , <a href="#">6AH</a> , <a href="#">6CH</a>
Character Device I/O	<a href="#">INT 29H</a> , <a href="#">INT 21H</a> : <a href="#">01H</a> , <a href="#">02H</a> , <a href="#">03H</a> , <a href="#">04H</a> , <a href="#">05H</a> , <a href="#">06H</a> , <a href="#">07H</a> , <a href="#">08H</a> , <a href="#">09H</a> , <a href="#">0AH</a> , <a href="#">0BH</a> , <a href="#">0AH</a> , <a href="#">0CH</a> , <a href="#">5D07H</a> , <a href="#">5D08H</a> , <a href="#">5D09H</a> , <a href="#">5D0AH</a>
Signals	<a href="#">INT 23H</a> , <a href="#">INT 24H</a> , <a href="#">INT 21H</a> : <a href="#">3300H</a> , <a href="#">3301H</a> , <a href="#">3302H</a>
Memory manager	<a href="#">INT 21H</a> : <a href="#">48H</a> , <a href="#">49H</a> , <a href="#">4AH</a> , <a href="#">5800H</a> , <a href="#">5801H</a> , <a href="#">5802H</a> , <a href="#">5803H</a>
Date and Time	<a href="#">INT 21H</a> : <a href="#">2AH</a> , <a href="#">2BH</a> , <a href="#">2CH</a> , <a href="#">2DH</a>
Misc	<a href="#">INT 21H</a> : <a href="#">30H</a> , <a href="#">3306H</a> , <a href="#">3700H</a> , <a href="#">3701H</a> , <a href="#">3702H</a> , <a href="#">3703H</a> , <a href="#">59H</a>
NLS	<a href="#">INT 21H</a> : <a href="#">3303H</a> , <a href="#">3304H</a> , <a href="#">3800H</a> , <a href="#">3801H</a> , <a href="#">6300H</a> , <a href="#">6301H</a> , <a href="#">6301H</a> , <a href="#">6500H</a> , <a href="#">6501H</a> , <a href="#">6502H</a> , <a href="#">6503H</a> , <a href="#">6504H</a> , <a href="#">6505H</a> , <a href="#">6506H</a> , <a href="#">6507H</a> , <a href="#">6520H</a> , <a href="#">6521H</a> , <a href="#">6522H</a> , <a href="#">6523H</a> , <a href="#">65A0H</a> , <a href="#">65A1H</a> , <a href="#">65A2H</a> , <a href="#">6601H</a> , <a href="#">6602H</a>
Devices	<a href="#">INT 21H</a> : <a href="#">4400H</a> , <a href="#">4401H</a> , <a href="#">4402H</a> , <a href="#">4403H</a> , <a href="#">4404H</a> , <a href="#">4405H</a> , <a href="#">4406H</a> , <a href="#">4407H</a> , <a href="#">4408H</a> , <a href="#">4409H</a> , <a href="#">440AH</a> , <a href="#">440BH</a> , <a href="#">440CH</a> , <a href="#">440DH</a> , <a href="#">440EH</a> , <a href="#">440FH</a> , <a href="#">4410H</a> , <a href="#">4411H</a> , <a href="#">53H</a>
Network	<a href="#">INT 21H</a> : <a href="#">5E00H</a> , <a href="#">5E01H</a> , <a href="#">5E02H</a> , <a href="#">5E03H</a> , <a href="#">5E04H</a> , <a href="#">5E05H</a> , <a href="#">5F00H</a> , <a href="#">5F01H</a> , <a href="#">5F02H</a> , <a href="#">5F03H</a> , <a href="#">5F04H</a> , <a href="#">5F05H</a> , <a href="#">5F07H</a> , <a href="#">5F08H</a>
<b>osFree Macro Library</b>	
Video I/O	<a href="#">@SetMode</a> <a href="#">@SetCurSz</a> <a href="#">@SetCurPos</a> <a href="#">@GetCur</a> <a href="#">@SetPage</a> <a href="#">@ScrollUp</a> <a href="#">@ScrollDn</a> <a href="#">@Scroll</a> <a href="#">@GetChAtr</a> <a href="#">@PutChAtr</a> <a href="#">@PutCh</a> <a href="#">@SetPalet</a> <a href="#">@SetColor</a> <a href="#">@SetDot</a> <a href="#">@GetDot</a> <a href="#">@WrtTTY</a> <a href="#">@VideoState</a> <a href="#">@GetMode</a> <a href="#">@GetDisplay</a> <a href="#">@GetVideoState</a> <a href="#">@GetEGAInfo</a> <a href="#">@Cls</a>
Hardware info	<a href="#">@Equipment</a> <a href="#">@MemSize</a>
Serial I/O	<a href="#">@AuxInit</a> <a href="#">@AuxSendChar</a> <a href="#">@AuxRecieveChar</a> <a href="#">@AuxStatus</a>
Tape I/O	<a href="#">@TapeOn</a> <a href="#">@TapeOff</a> <a href="#">@TapeRead</a> <a href="#">@TapeWrite</a>
Keyboard I/O	<a href="#">@KbdStatus</a> <a href="#">@CharIn</a> <a href="#">@CharPeek</a>
Printer I/O	<a href="#">@PrnPrint</a> <a href="#">@PrnInit</a> <a href="#">@PrnStatus</a>

<b>osFree Macro Library</b>	
Disk I/O	@DskReset @DskStatus @DskRead @DskWrite @DskVerify @DskFormat
Date and Time	@SetTime @GetTime
Mouse	@MouInit @MouShowPointer @MouStatus @MouSetPos @MouSetMickey @MouRegion
Memory manager	@ModBlok SET_BLOCK

2022/10/04 14:28 · prokushev · 0 Comments

2018/09/04 17:23 · prokushev · 0 Comments

<b>Family API</b>		
DOS	Process Manager	DosBeep DosExit DosSleep DosExecPgm
	File Manager	DosChDir DosChgFilePtr DosClose DosDelete DosDupHandle DosMkDir DosMove DosQCurDir DosQCurDisk DosSetFileMode DosOpen DosQFileInfo DosRead DosQFileMode DosQFSInfo DosQVerify DosRmDir DosSelectDisk DosFindClose DosFindFirst DosFindNext DosSetFileInfo DosSetVerify DosWrite DosFileLocks DosSetFHandState DosNewSize DosBufReset DosQFHandState DosSetFSInfo DosShutdown
	Memory Manager	DosFreeSeg DosSubAlloc DosSubFree DosSubSet DosAllocHuge DosAllocSeg DosReallocHuge DosReallocSeg DosGetHugeShift DosCreateCSAlias
	NLS	DosCaseMap DosGetCtryInfo DosGetDBCSEv DosSetCtryCode DosGetCollate DosGetMessage DosInsMessage DosPutMessage
	Date and Time	DosSetDateTime DosGetDateTime
	Devices	DosDevConfig DosDevIOct1 DosDevIOct2
	Signals	DosHoldSignal DosSetSigHandler
	Misc	BadDynLink DosGetEnv DosGetMachineMode DosGetVersion DosError DosErrClass DosSetVec
KBD	KbdCharIn KbdFlushBuffer KbdGetStatus KbdSetStatus KbdStringIn KbdPeek	
VIO	VioGetBuf VioGetConfig VioGetCurPos VioGetCurType VioGetPhysBuf VioReadCellStr VioReadCharStr VioScrollUp VioScrollDn VioScrollLf VioScrollRt VioScrUnLock VioSetCurPos VioSetCurType VioSetMode VioGetMode VioShowBuf VioWrtCellStr VioWrtCharStr VioWrtCharStrAtt VioWrtNAttr VioWrtNCell VioWrtNChar VioWrtTTY VioScrLock VioPopUp	
Tools	BIND	
Modules	DOSCALLS.DLL VIOCALLS.DLL KBDCALLS.DLL MSG.DLL	
Libraries	API.LIB OS2386.LIB FAPI.LIB DOSCALLS.LIB SUBCALLS.LIB	

2018/08/25 15:05 · prokushev · 0 Comments

From:

<https://cocorico.osfree.org/doku/> - **osFree wiki**

Permanent link:

<https://cocorico.osfree.org/doku/doku.php?id=en:docs:dos:api:int20&rev=1607406455>Last update: **2020/12/08 05:47**